

SPECIFICATION

Title of the Invention :

**IMAGE COMMUNICATION APPARATUS AND
DATA STORAGE METHOD**

Inventor(s) :

Shinichi KAWAI

09814707.032301

IMAGE COMMUNICATION APPARATUS AND DATA STORAGE METHOD

BACKGROUND OF THE INVENTION

5 Field of the Invention

The present invention relates to an image communication apparatus and a method of storing data thereof capable of rewriting a program stored in memory.

10 Description of the Related Art

A facsimile apparatus is conventionally known, which receives a new program from an external facsimile apparatus or external personal computer (hereinafter referred to as "PC") through a telephone line and
15 upgrades the apparatus by replacing a program stored inside the apparatus by the new program.

However, such a facsimile apparatus has a problem that in the case where the capacity of the new program exceeds the capacity of memory inside the apparatus, it
20 is impossible to store the new program in memory inside the apparatus or rewrite the program inside the apparatus.

SUMMARY OF THE INVENTION

25

It is an object of the present invention to provide an image communication apparatus and data storage method capable of reliably rewriting a program inside the

00014707.032301

apparatus with a program received through a telephone line by using expanded memory.

That is, the image communication apparatus and data storage method of the present invention compares the capacity of predetermined data received from a communication line with the capacity of existing memory in the apparatus, and in the case where the capacity of predetermined data exceeds the capacity of existing memory, determines the presence or absence of any expanded memory in the apparatus. In the case where there is expanded memory, the image communication apparatus and data storage method of the present invention compares the capacity of the expanded memory with the capacity of predetermined data and stores the predetermined data in the expanded memory when the capacity of the expanded memory exceeds the capacity of the predetermined data. In this way, the image communication apparatus and data storage method of the present invention determines not only the capacity of existing memory in the apparatus but also the presence or absence and capacity of expanded memory, and thereby determines whether or not to store the predetermined data received from the communication line, making it possible to reliably store the predetermined data in the apparatus.

BRIEF DESCRIPTION OF THE DRAWINGS

The above and other objects and features of the invention will appear more fully hereinafter from a consideration of the following description taken in connection with the accompanying drawing wherein one example is illustrated by way of example, in which;

FIG.1 is a block diagram showing an outlined configuration of a facsimile apparatus according to an embodiment of the present invention;

FIG.2 is a sequence diagram of transmission/reception of signals or data between the facsimile apparatus according to the embodiment above and a facsimile apparatus, which is a transmitter;

FIG.3 is a frame configuration diagram of an NSS signal sent by the facsimile apparatus, which is the transmitter, to the facsimile apparatus according to the embodiment above; and

FIG.4 is a flow chart when the facsimile apparatus according to an embodiment above rewrites a program.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

With reference now to the attached drawings, an embodiment of the present invention will be explained in detail below.

FIG.1 is a block diagram showing an outlined configuration of a facsimile apparatus according to an embodiment of the present invention. Facsimile

apparatus 100 according to this embodiment is provided with CPU 101 that controls the entire apparatus. This CPU 101 is connected with program FROM 103, DRAM 104, image FROM 105 and memory expansion slot 106 through control bus 102.

CPU 101 incorporates a RAM to store a program used when a program (hereinafter referred to as "present program") stored in program FROM 103 is rewritten. This prevents the function of facsimile apparatus 100 from stopping when the present program is rewritten.

Program FROM 103 stores a program to be executed by CPU 101. CPU 101 controls the aforementioned components of facsimile apparatus 100 through control bus 102 by executing this program. This allows facsimile apparatus 100 to implement the facsimile communication function.

DRAM 104 is used as work memory for CPU 101. DRAM 104 is also used as page memory to store one page of image data when facsimile apparatus 100 records images.

Image FROM 105 stores image data read by a scanner, which will be described later, and image data received through a telephone line network. Image FROM 105 stores a new program when the present program is rewritten.

Memory expansion slot 106 is a slot where a card memory such as FROM card 107, etc. is inserted. The memory capacity is expanded by inserting FROM card 107 in memory expansion slot 106. A new program and image data received through a telephone line network are stored

00004707 032304

Control bus 102 is also connected with printer control section 108, scanner control section 109 and panel control section 110.

10 Scanner control section 109 is connected to a
reading apparatus such as scanner 112 and controls this
scanner 112. Scanner 112 scans image data of a document
under the control of scanner control section 109.

Furthermore, control bus 102 is also connected with modem 114 and network control section 115.

Modem 114 communicates predetermined signals and image data through telephone line network 116. At this
25 time, network control section 115 controls transmission/reception of signals, etc. with telephone line network 116. Through this function of CPU 101 of controlling modem 114 and network control section 115,

facsimile apparatus 100 can perform facsimile communication with facsimile apparatus 117, etc., which is located in a remote place, through telephone line network 116.

5 Then, transmission/reception of signals or data by facsimile apparatus 100 in the above configuration when the program inside the apparatus is rewritten will be explained using the sequence diagram shown in FIG.2. In FIG.2, suppose facsimile apparatus 100 is a facsimile
10 apparatus on the receiver side that receives the program through telephone line network 116.

 When the program stored in program FROM 103 of facsimile apparatus 100 is rewritten, as shown in FIG.2, a call originating signal output from facsimile
15 apparatus on the transmitter side (hereinafter referred to as "transmitter") 200 is transmitted through telephone line network 116, converted to a calling signal by an exchange and output to facsimile apparatus 100.

 Upon reception of this calling signal, facsimile
20 apparatus 100 sends signals indicating ability (hereinafter referred to as "ability signal") such as a DIS signal indicating a standard function of facsimile apparatus 100, a CED signal to identify facsimile apparatus 100 and an NSF signal indicating a non-standard
25 function of facsimile apparatus 100 to transmitter 200.

 Upon reception of these ability signals, transmitter 200 sends an NSS signal indicating a transmission instruction as a response signal for the

09814707, 032301
T02220, 0241860

NSF signal, a DCS signal indicating a mode setting instruction as a response signal for the DIS signal and a TCF signal to check training to facsimile apparatus 100.

5 Here, the NSS signal sent by transmitter 200 as a response signal for the NSF signal from facsimile apparatus 100 will be explained using FIG.3. FIG.3 illustrates a frame configuration of the NSS signal sent by transmitter 200.

10 As shown in FIG.3, the frame of the NSS signal consists of a flag field (F) that indicates the beginning and end of the frame and is used to establish frame synchronization, an address field (A) used to transmit address information and a control field (C) used to
15 identify the function of the frame.

 Furthermore, the frame of the NSS signal includes a facsimile control field (FCF) to identify the function of a control signal. This facsimile control field (FCF) contains information identifiable as the NSS signal.

20 The frame of the NSS signal further includes a facsimile communication information field (FIF) to transmit function information, etc. of the transmitter. A flag indicating the program rewrite specification is set at a predetermined address of this facsimile
25 communication information field (FIF).

 Furthermore, the frame of the NSS signal includes a frame check sequence (FCS) to detect whether any transmission error exists or not from the address field

00014707-000001

(A) to the facsimile communication information field (FIF).

Then, upon reception of such response signals, facsimile apparatus 100 sends a CFR signal indicating
5 that transmission of program data is allowed to start to transmitter 200 as shown in FIG.2.

Upon reception of this CFR signal, transmitter 200 sends the program data to facsimile apparatus 100. Then, upon completion of the transmission of the program data,
10 transmitter 200 sends an EOP signal that indicates the end of transmission of the program data and that there is no subsequent data to facsimile apparatus 100.

Upon reception of this EOP signal, facsimile apparatus 100 sends an MCF signal indicating that the
15 program data has been received correctly to transmitter 200.

Then, transmitter 200 that has received this MCF signal sends a DCN signal indicating an instruction to disconnect the line that has been connected to facsimile
20 apparatus 100, thereby disconnecting the line and terminating transmission/reception of signals or data between transmitter 200 and facsimile apparatus 100 when the program is rewritten.

Then, the operation of facsimile apparatus 100 when
25 the present program is rewritten will be explained using FIG.4. FIG.4 is a flow chart when the program of facsimile apparatus 100 is rewritten.

When the program of facsimile apparatus 100 is

00814707.032301

rewritten, CPU 101 of facsimile apparatus 100 analyzes the frame of the NSS signal sent from transmitter 200 (ST 401) first and determines whether a flag indicating a program rewrite specification is set in the facsimile communication information field (FIF) of the frame of the NSS signal or not (ST 402).

In the case where the flag indicating a program rewrite specification is set in the facsimile communication information field (FIF) of the frame of the NSS signal, CPU 101 determines whether the memory capacity of image FROM 105 is larger than the memory capacity of program FROM 103 or not (ST 403). CPU 101 recognizes the memory capacities of image FROM 105 and program FROM 103 beforehand.

In this way, checking the memory capacity of image FROM 105 when the program is rewritten prevents facsimile apparatus 100 from failing to store the new program. By the way, suppose the capacity of the new program is equal to the memory capacity of program FROM 103.

In the case where the flag indicating a program rewrite specification is not set in the facsimile communication information field (FIF) of the frame of the NSS signal, CPU 101 performs normal facsimile communication and receives the image data sent from transmitter 200 (ST 404).

In ST 403, when the memory capacity of image FROM 105 is larger than the memory capacity of program FROM 103, CPU 101 specifies the address from which writing

00814707-032304

of the new program is started (ST 405). More specifically, CPU 101 specifies the start address of image FROM 105 as the address from which writing of the new program is started.

5 After specifying the start address of image FROM 105 as the address from which writing of the new program is started, CPU 101 receives program data via telephone line network 116 (ST 406). The received program data is stored in image FROM 105 under the control of CPU 101.

10 On the other hand, in ST 403, when the memory capacity of image FROM 105 is smaller than the memory capacity of program FROM 103, CPU 101 determines whether FROM card 107 is inserted in memory expansion slot 106 or not (ST 407). Here, suppose FROM card 107 is inserted
15 in memory expansion slot 106.

 After determining that FROM card 107 is inserted in memory expansion slot 106, CPU 101 determines whether the memory capacity of FROM card 107 is larger than the memory capacity of program FROM 103 or not (ST 408). By
20 the way, CPU 101 recognizes the memory capacity of this FROM card 107 beforehand when FROM card 107 is inserted.

 Thus, when the program is rewritten, if CPU 101 checks the memory capacity of image FROM 105 and determines that the new program cannot be stored, CPU
25 101 checks the memory capacity of FROM card 107 and thereby prevents facsimile apparatus 100 from failing to store the new program.

 In the case where the memory capacity of FROM card

107 is larger than the memory capacity of program FROM 103, CPU 101 specifies the address from which writing of the new program is started (ST 409). More specifically, CPU 101 specifies the start address of FROM card 107 as the address from which writing of the new program is started.

After specifying the start address of FROM card 107 as the address from which writing of the new program is started, CPU 101 receives program data via telephone line network 116 (ST 406). The program data received is stored in FROM card 107 under the control of CPU 101.

Then, in ST406, when the program data is stored in image FROM 105 or FROM card 107, CPU 101 executes the program of rewriting the present program stored in the built-in RAM. This allows the present program to be rewritten with the new program.

On the other hand, when the memory capacity of FROM card 107 is smaller than the memory capacity of program FROM 103, CPU 101 determines that the capacity of the present memory of facsimile apparatus 100 is too small to store the new program and disconnects the line that has been connected with transmitter 200 (ST 410).

Moreover, in ST 407 when CPU 101 determines that FROM card 107 is not inserted in memory expansion slot 106, CPU 101 also determines that the capacity of the present memory of facsimile apparatus 100 is too small to store the new program and disconnects the line that has been connected with transmitter 200 (ST 410).

10

25

described embodiments, and various variations and modifications may be possible without departing from the scope of the present invention.

This application is based on the Japanese Patent
5 Application No.2000-099211 filed on March 31, 2000,
entire content of which is expressly incorporated by
reference herein.

00014707:032301